

CPX 436IP

4 Modes 6 - 9 - 84 - 89

6 CHs

| Channel | Function | Value | Description |
|---------|----------|-----------|-----------------------------|
| 1 | Dimmer | 0 --> 255 | 0% to 100% Dimmer |
| 2 | Strobe | 0 --> 255 | Slow to Fast Strobe |
| 3 | Red | 0 --> 255 | 0% to 100% Red LEDs |
| 4 | Green | 0 --> 255 | 0% to 100% Green LEDs |
| 5 | Blue | 0 --> 255 | 0% to 100% Blue LEDs |
| 6 | Amber | 0 --> 255 | 0% to 100% Amber Beams LEDs |

9 CHs

| Channel | Function | Value | Description |
|---------|------------------|-----------|-----------------------------|
| 1 | Dimmer | 0 --> 255 | 0% to 100% Dimmer |
| 2 | Strobe | 0 --> 255 | Slow to Fast Strobe |
| 3 | Red | 0 --> 255 | 0% to 100% Red LEDs |
| 4 | Green | 0 --> 255 | 0% to 100% Green LEDs |
| 5 | Blue | 0 --> 255 | 0% to 100% Blue LEDs |
| 6 | Amber | 0 --> 255 | 0% to 100% Amber Beams LEDs |
| 7 | Different Colors | 0 | Safe |
| | | 1 --> 255 | Different Colors Macros |
| 8 | Macro | 0 | Safe |
| | | 1 --> 255 | Macro Selection |
| 9 | Speed | 0 --> 255 | Effect Speed |

84 CHs

| Channel | Function | Value | Description |
|---------|----------|-----------|-------------------------------|
| 1 | Amber | 0 --> 255 | 0% to 100% B1 Amber Beam LED |
| 2 | Amber | 0 --> 255 | 0% to 100% B2 Amber Beam LED |
| 3 | Amber | 0 --> 255 | 0% to 100% B3 Amber Beam LED |
| ... | ... | ... | ... |
| 11 | Amber | 0 --> 255 | 0% to 100% B11 Amber Beam LED |
| 12 | Amber | 0 --> 255 | 0% to 100% B12 Amber Beam LED |
| 13 | Red | 0 --> 255 | 0% to 100% Cell 1 Red LEDs |
| 14 | Green | 0 --> 255 | 0% to 100% Cell 1 Green LEDs |
| 15 | Blue | 0 --> 255 | 0% to 100% Cell 1 Blue LEDs |
| 16 | Red | 0 --> 255 | 0% to 100% Cell 2 Red LEDs |
| 17 | Green | 0 --> 255 | 0% to 100% Cell 2 Green LEDs |
| 18 | Blue | 0 --> 255 | 0% to 100% Cell 2 Blue LEDs |
| 19 | Red | 0 --> 255 | 0% to 100% Cell 3 Red LEDs |
| 20 | Green | 0 --> 255 | 0% to 100% Cell 3 Green LEDs |
| 21 | Blue | 0 --> 255 | 0% to 100% Cell 3 Blue LEDs |
| ... | ... | ... | ... |
| 79 | Red | 0 --> 255 | 0% to 100% Cell 23 Red LEDs |
| 80 | Green | 0 --> 255 | 0% to 100% Cell 23 Green LEDs |
| 81 | Blue | 0 --> 255 | 0% to 100% Cell 23 Blue LEDs |
| 82 | Red | 0 --> 255 | 0% to 100% Cell 24 Red LEDs |
| 83 | Green | 0 --> 255 | 0% to 100% Cell 24 Green LEDs |
| 84 | Blue | 0 --> 255 | 0% to 100% Cell 24 Blue LEDs |

89 CHs

| Channel | Function | Value | Description |
|---------|------------------|-----------|-------------------------------|
| 1 | Dimmer | 0 --> 255 | 0% to 100% Dimmer |
| 2 | Strobe | 0 --> 255 | Slow to Fast Strobe |
| 3 | Amber | 0 --> 255 | 0% to 100% B1 Amber Beam LED |
| 4 | Amber | 0 --> 255 | 0% to 100% B2 Amber Beam LED |
| 5 | Amber | 0 --> 255 | 0% to 100% B3 Amber Beam LED |
| ... | ... | ... | ... |
| 13 | Amber | 0 --> 255 | 0% to 100% B11 Amber Beam LED |
| 14 | Amber | 0 --> 255 | 0% to 100% B12 Amber Beam LED |
| 15 | Red | 0 --> 255 | 0% to 100% Cell 1 Red LEDs |
| 16 | Green | 0 --> 255 | 0% to 100% Cell 1 Green LEDs |
| 17 | Blue | 0 --> 255 | 0% to 100% Cell 1 Blue LEDs |
| 18 | Red | 0 --> 255 | 0% to 100% Cell 2 Red LEDs |
| 19 | Green | 0 --> 255 | 0% to 100% Cell 2 Green LEDs |
| 20 | Blue | 0 --> 255 | 0% to 100% Cell 2 Blue LEDs |
| 21 | Red | 0 --> 255 | 0% to 100% Cell 3 Red LEDs |
| 22 | Green | 0 --> 255 | 0% to 100% Cell 3 Green LEDs |
| 23 | Blue | 0 --> 255 | 0% to 100% Cell 3 Blue LEDs |
| ... | ... | ... | ... |
| 81 | Red | 0 --> 255 | 0% to 100% Cell 23 Red LEDs |
| 82 | Green | 0 --> 255 | 0% to 100% Cell 23 Green LEDs |
| 83 | Blue | 0 --> 255 | 0% to 100% Cell 23 Blue LEDs |
| 84 | Red | 0 --> 255 | 0% to 100% Cell 24 Red LEDs |
| 85 | Green | 0 --> 255 | 0% to 100% Cell 24 Green LEDs |
| 86 | Blue | 0 --> 255 | 0% to 100% Cell 24 Blue LEDs |
| 87 | Different Colors | 0 | Safe |
| | | 1 --> 255 | Different Colors Macros |
| 88 | Macro | 0 | Safe |
| | | 1 --> 255 | Macro Selection |
| 89 | Speed | 0 --> 255 | Effect Speed |