



## Flash 88

5 Modes 2 - 3 - 4 - 9 - 12

2 CHs

Channel	Function	Value
1	Color Macro	0 --> 255
2	White Macro	0 --> 255

3 Ch

Channel	Function	Value
1	Hue	0 --> 255
2	Saturation	0 --> 255
3	Dimmer	0 --> 255

4 CHs

Channel	Function	Value
1	Red	0 --> 255
2	Green	0 --> 255
3	Blue	0 --> 255
4	White	0 --> 255

9 CHs

Channel	Function	Value
1	Dimmer	0 --> 255
2	Dimmer Modes	0 --> 49
		50 --> 99
		100 --> 149
		150 --> 199
		200 --> 255
3	Red	0 --> 255
4	Green	0 --> 255
5	Blue	0 --> 255
6	White	0 --> 255
7	Strobe	0 --> 255
		0

8	Auto Program	8 --> 10
		11 --> 20
		21 --> 30
		31 --> 40
		41 --> 50
		51 --> 60
		61 --> 70
		71 --> 80
		81 --> 90
		91 --> 100
		101 --> 110
		111 --> 120
		121 --> 130
		131 --> 140
		141 --> 150
		151 --> 160
		161 --> 170
171 --> 180		
181 --> 190		
200 --> 255		
9	Speed	0 --> 255

12 CHs

Channel	Function	Value
1	Dimmer	0 --> 255
2	Dimmer Modes	0 --> 49
		50 --> 99
		100 --> 149
		150 --> 199
		200 --> 255
3	Red	0 --> 255
4	Green	0 --> 255
5	Blue	0 --> 255
6	White	0 --> 255
7	Strobe	0 --> 5
		6 --> 10
		11 --> 33
		34 --> 56
		57 --> 79
		80 --> 102
		103 --> 127
		128 --> 250
		251 --> 255
8	Color Macro	0 --> 255
9	White Macro	0 --> 255
		0

10	Auto Program	8 --> 10
		11 --> 20
		21 --> 30
		31 --> 40
		41 --> 50
		51 --> 60
		61 --> 70
		71 --> 80
		81 --> 90
		91 --> 100
		101 --> 110
		111 --> 120
		121 --> 130
		131 --> 140
		141 --> 150
		151 --> 160
		161 --> 170
171 --> 180		
181 --> 190		
200 --> 255		
11	Speed	0 --> 255
12	ID	0 --> 255

<b>Description</b>
72 Color Macros
11 White Macros

<b>Description</b>
0% to 100% Color Hue
0% to 100% Color Saturation
0% to 100% Dimmer

<b>Description</b>
0% to 100% Red LEDs
0% to 100% Green LEDs
0% to 100% Blue LEDs
0% to 100% White LEDs

<b>Description</b>
0% to 100% Dimmer
Default Dimmer
Dimmer Mode 1
Dimmer Mode 2
Dimmer Mode 3
Dimmer Mode 4
0% to 100% Red LEDs
0% to 100% Green LEDs
0% to 100% Blue LEDs
0% to 100% White LEDs
0 Hz to 20Hz Strobe
Default

Program 1
Program 2
Program 3
Program 4
Program 5
Program 6
Program 7
Program 8
Program 9
Custom 1
Custom 2
Custom 3
Custom 4
Custom 5
Custom 6
Custom 7
Custom 8
Custom 9
Custom 10
Custom 11
Program Speed when Enabled

<b>Description</b>
0% to 100% Dimmer
Default Dimmer
Dimmer Mode 1
Dimmer Mode 2
Dimmer Mode 3
Dimmer Mode 4
0% to 100% Red LEDs
0% to 100% Green LEDs
0% to 100% Blue LEDs
0% to 100% White LEDs
Open
Close
Slow to Fast Random Pulse
Slow to Fast Ramp up
Slow to Fast Ramp Down
Slow to Fast Random Strobe
Strobe Burst 5s - 1s
0 Hz to 20Hz Strobe
Open
72 Color Macros
11 White Macros
Default

Program 1
Program 2
Program 3
Program 4
Program 5
Program 6
Program 7
Program 8
Program 9
Custom 1
Custom 2
Custom 3
Custom 4
Custom 5
Custom 6
Custom 7
Custom 8
Custom 9
Custom 10
Custom 11
Program Speed when Enabled
ID Address Set