

BAT 606

2 Modes 6 - 10

6 CHs

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Green	0 --> 255	0% to 100% Green LEDs
3	Blue	0 --> 255	0% to 100% Blue LEDs
4	White	0 --> 255	0% to 100% White LEDs
5	Amber	0 --> 255	0% to 100% Amber LEDs
6	UV	0 --> 255	0% to 100% UV LEDs

10 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 9	Open
		10 --> 255	Slow to Fast Strobe
3	Red	0 --> 255	0% to 100% Red LEDs
4	Green	0 --> 255	0% to 100% Green LEDs
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	White	0 --> 255	0% to 100% White LEDs
7	Amber	0 --> 255	0% to 100% Amber LEDs
8	UV	0 --> 255	0% to 100% UV LEDs
9	Macro	0 --> 50	Safe
		170 --> 209	Sound Color Jump
		210 --> 239	Sound Pulse + Strobe
		240 --> 255	Sound Strobe
8	Speed	0 --> 255	Dimmer Speed / Macro Effect Speed