

Strobe 1200

6 Modes 1 - 2 - 3 - 4 - 6 - 7

1 Ch

Channel	Function	Value	Description
1	Strobe	0 --> 5	Safe
		6 --> 255	0.3-25 HZ @50HZAC 0.4-30 HZ @60HZAC

2 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 5	Close
		6 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Safe
		6 --> 255	0.3-25 HZ @50HZAC 0.4-30 HZ @60HZAC

3 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 5	Close
		6 --> 255	0% to 100% Dimmer
2	Duration	0 --> 255	0-650ms @50HZAC 0-530ms @60HZAC
3	Strobe	0 --> 5	Safe
		6 --> 255	0.3-25 HZ @50HZAC 0.4-30 HZ @60HZAC

4 Ch

Channel	Function	Value	Description
1	Dimmer	0 --> 5	Close
		6 --> 255	0% to 100% Dimmer
2	Duration	0 --> 255	0-650ms @50HZAC 0-530ms @60HZAC
3	Strobe	0 --> 5	Safe
		6 --> 255	0.3-25 HZ @50HZAC 0.4-30 HZ @60HZAC
4	Effect	0 --> 5	Safe
		6 --> 55	Fade In
		56 --> 105	Fade Out
		106 --> 155	Bounce In/Out
		156 --> 205	Light Effect
		206 --> 255	Random Strobe

6 Ch

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Green	0 --> 255	0% to 100% Green LEDs
3	Blue	0 --> 255	0% to 100% Blue LEDs
4	Dimmer	0 --> 5	Close
		6 --> 255	0% to 100% Dimmer
5	Duration	0 --> 255	0-650ms @50HZAC 0-530ms @60HZAC
6	Strobe	0 --> 5	Safe
		6 --> 255	0.3-25 HZ @50HZAC 0.4-30 HZ @60HZAC

7 Ch

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Green	0 --> 255	0% to 100% Green LEDs
3	Blue	0 --> 255	0% to 100% Blue LEDs
4	Dimmer	0 --> 5	Close
		6 --> 255	0% to 100% Dimmer
5	Duration	0 --> 255	0-650ms @50HZAC 0-530ms @60HZAC
6	Strobe	0 --> 5	Safe
		6 --> 255	0.3-25 HZ @50HZAC 0.4-30 HZ @60HZAC
7	Effect	0 --> 5	Safe
		6 --> 55	Fade In
		56 --> 105	Fade Out
		106 --> 155	Bounce In/Out
		156 --> 205	Light Effect
		206 --> 255	Random Strobe