

## Strobe 300

5 Modes 9 - 11 - 18 - 39 -55

9 Ch
------

Channel	Function	Value	Description
1	Program Macro	0 --> 39	Safe
		40 --> 43	Macro 1
		44 --> 47	Macro 2
		48 --> 51	Macro 3
		52 --> 55	Macro 4
		56 --> 59	Macro 5
		60 --> 63	Macro 6
		64 --> 67	Macro 7
		68 --> 71	Macro 8
		72 --> 75	Macro 9
		76 --> 79	Macro 10
		80 --> 83	Macro 11
		84 --> 87	Macro 12
		88 --> 91	Macro 13
		92 --> 95	Macro 14
		96 --> 99	Macro 15
		100 --> 103	Macro 16
		104 --> 107	Macro 17
		108 --> 111	Macro 18
		112 --> 115	Macro 19
		116 --> 119	Macro 20
		120 --> 123	Macro 21
		124 --> 127	Macro 22
		128 --> 131	Macro 23
		132 --> 135	Macro 24
		136 --> 139	Macro 25
		140 --> 143	Macro 26
		144 --> 147	Macro 27
		148 --> 151	Macro 28
		152 --> 155	Macro 29
156 --> 159	Macro 30		

		160 --> 163	Macro 31
		164 --> 167	Macro 32
		168 --> 171	Macro 33
		172 --> 175	Macro 34
		176 --> 179	Macro 35
		180 --> 183	Macro 36
		184 --> 187	Macro 37
		188 --> 191	Macro 38
		192 --> 195	Macro 39
		196 --> 199	Macro 40
		200 --> 203	Macro 41
		204 --> 207	Macro 42
		208 --> 211	Macro 43
		212 --> 215	Macro 44
		216 --> 219	Macro 45
		220 --> 223	Macro 46
		224 --> 227	Macro 47
		228 --> 231	Macro 48
		232 --> 235	Macro 49
		236 --> 239	Macro 50
		240 --> 243	Macro 51
		244 --> 247	Macro 52
		248 --> 251	Macro 53
		252 --> 255	Macro 54
2	Macro Speed / / Sound	0 --> 250	Slow to Fast Macro Speed
		251 --> 255	Sound Mode
3	Dimmer	0 --> 255	0% to 100% Dimmer
4	White Strobe	0 --> 15	Safe
		16 --> 115	Slow to Fast Pulse
		116 --> 135	Off
		136 --> 235	Slow to Fast Random Strobe
		236 --> 255	Off
5	RGB Strobe	0 --> 15	Safe
		16 --> 115	Slow to Fast Pulse
		116 --> 135	Off
		136 --> 235	Slow to Fast Random Strobe
		236 --> 255	Off
6	White	0 --> 255	0% to 100% White LEDs
7	Red	0 --> 255	0% to 100% Red LEDs
8	Green	0 --> 255	0% to 100% Green LEDs
9	Blue	0 --> 255	0% to 100% Blue LEDs

Channel	Function	Value	Description
1	White Dimmer	0 --> 255	0% to 100% Dimmer
2	White Strobe Duration	0 --> 255	Fast to Slow Duration
3	White Macro Speed	0 --> 255	Slow to Fast Macro
4	White Macros	0 --> 24	Safe
		25 --> 35	White Fade
		36 --> 46	White Random Fade
		47 --> 57	Reverse White Fade
		58 --> 68	Reverse White Random Fade
		69 --> 79	White Bounce Fade
		80 --> 90	White Random Bounce Fade
		91 --> 101	Normal
		102 --> 112	White Random on Pixel
		113 --> 123	Left to Right 1 Pixel On
		124 --> 134	Right to Left 1 Pixel On
		135 --> 145	Left to Right 1 Pixel Off
		146 --> 156	Right to Left 1 Pixel Off
		157 --> 167	Left to Right 2 Pixels On
		168 --> 178	Right to Left 2 Pixels Off
		179 --> 189	Left to Right Effect
		190 --> 200	Right to Left Effect
201 --> 211	Left to Right Filling		
212 --> 222	Right to Left Filling		
223 --> 233	Left to Right 1 Pixel Strobe		
234 --> 244	Right to Left 1 Pixel Strobe		
245 --> 255	Mixed Macros		
5	RGB	0 --> 255	0% to 100% RGB Dimmer
6	RGB Strobe Duration	0 --> 255	Fast to Slow Duration
7	RGB Macro Speed	0 --> 255	Slow to Fast Macro

8	RGB Macros	0 --> 24	Safe
		25 --> 35	White Fade
		36 --> 46	White Random Fade
		47 --> 57	Reverse White Fade
		58 --> 68	Reverse White Random Fade
		69 --> 79	White Bounce Fade
		80 --> 90	White Random Bounce Fade
		91 --> 101	Normal
		102 --> 112	White Random on Pixel
		113 --> 123	Left to Right 1 Pixel On
		124 --> 134	Right to Left 1 Pixel On
		135 --> 145	Left to Right 1 Pixel Off
		146 --> 156	Right to Left 1 Pixel Off
		157 --> 167	Left to Right 2 Pixels On
		168 --> 178	Right to Left 2 Pixels Off
		179 --> 189	Left to Right Effect
		190 --> 200	Right to Left Effect
		201 --> 211	Left to Right Filling
		212 --> 222	Right to Left Filling
		223 --> 233	Left to Right 1 Pixel Strobe
234 --> 244	Right to Left 1 Pixel Strobe		
245 --> 255	Mixed Macros		
9	Red	0 --> 255	0% to 100% Red LEDs
10	Green	0 --> 255	0% to 100% Green LEDs
11	Blue	0 --> 255	0% to 100% Blue LEDs

18 Ch
-------

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	White Strobe	0 --> 15	Safe
		16 --> 115	Slow to Fast Pulse
		116 --> 135	Off
		136 --> 235	Slow to Fast Random Strobe
		236 --> 255	Off
3	RGB Strobe	0 --> 15	Safe
		16 --> 115	Slow to Fast Pulse
		116 --> 135	Off
		136 --> 235	Slow to Fast Random Strobe
		236 --> 255	Off
4	White Dimmer	0 --> 255	0% to 100% Dimmer
5	White Strobe Duration	0 --> 255	Fast to Slow Duration
6	White Macro Speed	0 --> 255	Slow to Fast Macro

7	White Macros	0 --> 24	Safe
		25 --> 35	White Fade
		36 --> 46	White Random Fade
		47 --> 57	Reverse White Fade
		58 --> 68	Reverse White Random Fade
		69 --> 79	White Bounce Fade
		80 --> 90	White Randome Bounce Fade
		91 --> 101	Normal
		102 --> 112	White Random on Pixel
		113 --> 123	Left to Right 1 Pixel On
		124 --> 134	Right to Left 1 Pixel On
		135 --> 145	Left to Right 1 Pixel Off
		146 --> 156	Right to Left 1 Pixel Off
		157 --> 167	Left to Right 2 Pixels On
		168 --> 178	Right to Left 2 Pixels Off
		179 --> 189	Left to Right Effect
		190 --> 200	Right to Left Effect
		201 --> 211	Left to Right Filling
		212 --> 222	Right to Left Filling
		223 --> 233	Left to Right 1 Pixel Strobe
234 --> 244	Right to Left 1 Pixel Strobe		
245 --> 255	Mixed Macros		
8	RGB	0 --> 255	0% to 100% RGB Dimmer
9	RGB Strobe Duration	0 --> 255	Fast to Slow Duration
10	RGB Macro Speed	0 --> 255	Slow to Fast Macro
11	RGB Macros	0 --> 24	Safe
		25 --> 35	White Fade
		36 --> 46	White Random Fade
		47 --> 57	Reverse White Fade
		58 --> 68	Reverse White Random Fade
		69 --> 79	White Bounce Fade
		80 --> 90	White Randome Bounce Fade
		91 --> 101	Normal
		102 --> 112	White Random on Pixel
		113 --> 123	Left to Right 1 Pixel On
		124 --> 134	Right to Left 1 Pixel On
		135 --> 145	Left to Right 1 Pixel Off
		146 --> 156	Right to Left 1 Pixel Off
		157 --> 167	Left to Right 2 Pixels On
		168 --> 178	Right to Left 2 Pixels Off
		179 --> 189	Left to Right Effect
		190 --> 200	Right to Left Effect
		201 --> 211	Left to Right Filling
		212 --> 222	Right to Left Filling
		223 --> 233	Left to Right 1 Pixel Strobe
234 --> 244	Right to Left 1 Pixel Strobe		
245 --> 255	Mixed Macros		

12	Macro Red	0 --> 255	0% to 100% Red
13	Macro Green	0 --> 255	0% to 100% Green
14	Macro Blue	0 --> 255	0% to 100% Blue
15	Back White	0 --> 255	0% to 100% White LEDs
16	Back Red	0 --> 255	0% to 100% Red LEDs
17	Back Green	0 --> 255	0% to 100% Green LEDs
18	Back Blue	0 --> 255	0% to 100% Blue LEDs

### 39 Ch

Channel	Function	Value	Description
1	White 1	0 --> 255	0% to 100% White LED
2	White 2	0 --> 255	0% to 100% White LED
3	White 3	0 --> 255	0% to 100% White LED
4	Red 1	0 --> 255	0% to 100% Red LEDs
5	Green 1	0 --> 255	0% to 100% Green LEDs
6	Blue 1	0 --> 255	0% to 100% Blue LEDs
7	Red 2	0 --> 255	0% to 100% Red LEDs
8	Green 2	0 --> 255	0% to 100% Green LEDs
9	Blue 2	0 --> 255	0% to 100% Blue LEDs
10	Red 3	0 --> 255	0% to 100% Red LEDs
11	Green 3	0 --> 255	0% to 100% Green LEDs
12	Blue 3	0 --> 255	0% to 100% Blue LEDs
...	...	...	...
31	Red 10	0 --> 255	0% to 100% Red LEDs
32	Green 10	0 --> 255	0% to 100% Green LEDs
33	Blue 10	0 --> 255	0% to 100% Blue LEDs
34	Red 11	0 --> 255	0% to 100% Red LEDs
35	Green 11	0 --> 255	0% to 100% Green LEDs
36	Blue 11	0 --> 255	0% to 100% Blue LEDs
37	Red 12	0 --> 255	0% to 100% Red LEDs
38	Green 12	0 --> 255	0% to 100% Green LEDs
39	Blue 12	0 --> 255	0% to 100% Blue LEDs

### 55 Ch

Channel	Function	Value	Description
		0 --> 39	Safe
		40 --> 43	Macro 1
		44 --> 47	Macro 2
		48 --> 51	Macro 3
		52 --> 55	Macro 4
		56 --> 59	Macro 5
		60 --> 63	Macro 6
		64 --> 67	Macro 7
		68 --> 71	Macro 8
		72 --> 75	Macro 9
		76 --> 79	Macro 10

1	Program Macro	80 --> 83	Macro 11		
		84 --> 87	Macro 12		
		88 --> 91	Macro 13		
		92 --> 95	Macro 14		
		96 --> 99	Macro 15		
		100 --> 103	Macro 16		
		104 --> 107	Macro 17		
		108 --> 111	Macro 18		
		112 --> 115	Macro 19		
		116 --> 119	Macro 20		
		120 --> 123	Macro 21		
		124 --> 127	Macro 22		
		128 --> 131	Macro 23		
		132 --> 135	Macro 24		
		136 --> 139	Macro 25		
		140 --> 143	Macro 26		
		144 --> 147	Macro 27		
		148 --> 151	Macro 28		
		152 --> 155	Macro 29		
		156 --> 159	Macro 30		
		160 --> 163	Macro 31		
		164 --> 167	Macro 32		
		168 --> 171	Macro 33		
		172 --> 175	Macro 34		
		176 --> 179	Macro 35		
		180 --> 183	Macro 36		
		184 --> 187	Macro 37		
		188 --> 191	Macro 38		
		192 --> 195	Macro 39		
		196 --> 199	Macro 40		
		200 --> 203	Macro 41		
		204 --> 207	Macro 42		
		208 --> 211	Macro 43		
		212 --> 215	Macro 44		
		216 --> 219	Macro 45		
		220 --> 223	Macro 46		
		224 --> 227	Macro 47		
		228 --> 231	Macro 48		
		232 --> 235	Macro 49		
		236 --> 239	Macro 50		
		240 --> 243	Macro 51		
		244 --> 247	Macro 52		
		248 --> 251	Macro 53		
		252 --> 255	Macro 54		
		2	Macro Speed / / Sound	0 --> 250	Slow to Fast Macro Speed
				251 --> 255	Sound Mode
		3	Dimmer	0 --> 255	0% to 100% Dimmer

4	White Strobe	0 --> 15	Safe
		16 --> 115	Slow to Fast Pulse
		116 --> 135	Off
		136 --> 235	Slow to Fast Random Strobe
		236 --> 255	Off
5	RGB Strobe	0 --> 15	Safe
		16 --> 115	Slow to Fast Pulse
		116 --> 135	Off
		136 --> 235	Slow to Fast Random Strobe
		236 --> 255	Off
6	White Dimmer	0 --> 255	0% to 100% Dimmer
7	White Strobe Duration	0 --> 255	Fast to Slow Duration
8	White Macro Speed	0 --> 255	Slow to Fast Macro
9	White Macros	0 --> 24	Safe
		25 --> 35	White Fade
		36 --> 46	White Random Fade
		47 --> 57	Reverse White Fade
		58 --> 68	Reverse White Random Fade
		69 --> 79	White Bounce Fade
		80 --> 90	White Random Bounce Fade
		91 --> 101	Normal
		102 --> 112	White Random on Pixel
		113 --> 123	Left to Right 1 Pixel On
		124 --> 134	Right to Left 1 Pixel On
		135 --> 145	Left to Right 1 Pixel Off
		146 --> 156	Right to Left 1 Pixel Off
		157 --> 167	Left to Right 2 Pixels On
		168 --> 178	Right to Left 2 Pixels Off
		179 --> 189	Left to Right Effect
		190 --> 200	Right to Left Effect
		201 --> 211	Left to Right Filling
		212 --> 222	Right to Left Filling
223 --> 233	Left to Right 1 Pixel Strobe		
234 --> 244	Right to Left 1 Pixel Strobe		
245 --> 255	Mixed Macros		
10	RGB	0 --> 255	0% to 100% RGB Dimmer
11	RGB Strobe Duration	0 --> 255	Fast to Slow Duration
12	RGB Macro Speed	0 --> 255	Slow to Fast Macro



13	RGB Macros	0 --> 24	Safe
		25 --> 35	White Fade
		36 --> 46	White Random Fade
		47 --> 57	Reverse White Fade
		58 --> 68	Reverse White Random Fade
		69 --> 79	White Bounce Fade
		80 --> 90	White Random Bounce Fade
		91 --> 101	Normal
		102 --> 112	White Random on Pixel
		113 --> 123	Left to Right 1 Pixel On
		124 --> 134	Right to Left 1 Pixel On
		135 --> 145	Left to Right 1 Pixel Off
		146 --> 156	Right to Left 1 Pixel Off
		157 --> 167	Left to Right 2 Pixels On
		168 --> 178	Right to Left 2 Pixels Off
		179 --> 189	Left to Right Effect
		190 --> 200	Right to Left Effect
		201 --> 211	Left to Right Filling
		212 --> 222	Right to Left Filling
		223 --> 233	Left to Right 1 Pixel Strobe
234 --> 244	Right to Left 1 Pixel Strobe		
245 --> 255	Mixed Macros		
14	Macro Red	0 --> 255	0% to 100% Red
15	Macro Green	0 --> 255	0% to 100% Green
16	Macro Blue	0 --> 255	0% to 100% Blue
17	White 1	0 --> 255	0% to 100% White LED
18	White 2	0 --> 255	0% to 100% White LED
19	White 3	0 --> 255	0% to 100% White LED
20	Red 1	0 --> 255	0% to 100% Red LEDs
21	Green 1	0 --> 255	0% to 100% Green LEDs
22	Blue 1	0 --> 255	0% to 100% Blue LEDs
23	Red 2	0 --> 255	0% to 100% Red LEDs
24	Green 2	0 --> 255	0% to 100% Green LEDs
25	Blue 2	0 --> 255	0% to 100% Blue LEDs
26	Red 3	0 --> 255	0% to 100% Red LEDs
27	Green 3	0 --> 255	0% to 100% Green LEDs
28	Blue 3	0 --> 255	0% to 100% Blue LEDs
...	...	...	...
47	Red 10	0 --> 255	0% to 100% Red LEDs
48	Green 10	0 --> 255	0% to 100% Green LEDs
49	Blue 10	0 --> 255	0% to 100% Blue LEDs
50	Red 11	0 --> 255	0% to 100% Red LEDs
51	Green 11	0 --> 255	0% to 100% Green LEDs
52	Blue 11	0 --> 255	0% to 100% Blue LEDs
53	Red 12	0 --> 255	0% to 100% Red LEDs
54	Green 12	0 --> 255	0% to 100% Green LEDs
55	Blue 12	0 --> 255	0% to 100% Blue LEDs