









FLASH 401 RGB is an audience blinder and strobe with four 100 watts RGB COB LED sources. Every 2 LEDs are in an independant housing that can be rotated and directed easily. Each of the 4 LEDs is controlled separately adding a dynamic chase pixel mapping effect alongside the blinder and electronic strobe effect. It delivers a powerful output making it ideal for any size indoor stage, clubs and entertainment lighting installation.

SOURCE Light source: 4 x 100 watts RGB COB LEDs

LED life expectancy: 50,000 Hrs.

OPTICAL SYSTEM

Beam angle: 40°

DYNAMIC Dimmer: Linear adjustment

EFFECTS Electronic strobe 4 zones control

CONTROL & Control protocols: DMX, Sound, Master-Slave, Auto Run PROGRAMMING Control channels: 2, 8 CHs

ELECTRICAL Input voltage: AC100-240V/50-60Hz

Power consumption: 400 watts

CONNECTIONS DMX connections: 3 pin and 5 pin XLR In/Out male and female

Power connections: PowerCon In/Out

PHYSICAL Dimensions: 400 x 400 x 200mm

Net weight: 11 Kg Color: Black Housing: Aluminum

IP rating: 20

Dimensions

