

## Zoom 19-II

5 Modes 10 - 21 - 8 -21 - 34

Person 1 : 10 Ch

Channel	Function	Value	Description
1	Pan	0 --> 255	540° Pan
2	Tilt	0 --> 255	270° Tilt
3	Red	0 --> 255	0% to 100% Red LEDs
4	Green	0 --> 255	0% to 100% Green LEDs
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	White	0 --> 255	0% to 100% White LEDs
7	Dimmer	0 --> 255	0% to 100% Dimmer
8	Strobe	0 --> 9	Safe
		10 --> 255	0 Hz to 20Hz Strobe
9	Zoom	0 --> 255	0% to 100% Zoom
10	Control	0 --> 19	Safe
		20 --> 39	Move in Dark ON
		40 --> 59	Move in Dark OFF
		60 --> 79	Fan Auto
		80 --> 99	Fan Slow
		100 --> 119	Fan Normal
		120 --> 139	Fan Fast
		140 --> 149	Auto 1
		150 --> 159	Auto 2
		160 --> 169	Test
		170 --> 179	Custom
		180 --> 199	Safe
		200 --> 219	Reset
		220 --> 235	Safe
		236 --> 239	Dim 0
		240 --> 243	Dim 1
		244 --> 247	Dim 2
248 --> 251	Dim 3		
252 --> 255	Dim 4		

Person 2 : 21 Ch

Channel	Function	Value	Description
1	Pan	0 --> 255	540° Pan
2	Pan Fine	0 --> 255	Pan Fine
3	Tilt	0 --> 255	270° Tilt
4	Tilt Fine	0 --> 255	Tilt Fine
5	P/T Speed	0 --> 255	Pan and Tilt Speed
6	Red	0 --> 255	0% to 100% Red LEDs
7	Red Fine	0 --> 255	Red Fine
8	Green	0 --> 255	0% to 100% Green LEDs
9	Green Fine	0 --> 255	Green Fine
10	Blue	0 --> 255	0% to 100% Blue LEDs
11	Blue Fine	0 --> 255	Blue Fine
12	White	0 --> 255	0% to 100% White LEDs
13	White Fine	0 --> 255	White Fine
14	Color Macro	0 --> 10	Open
		11 --> 200	Index
		201 --> 205	White 1 : 3200 K
		206 --> 210	White 2 : 3400 K
		211 --> 215	White 3 : 4200 K
		216 --> 220	White 4 : 4900 K
		221 --> 225	White 5 : 5600 K
		226 --> 230	White 6 : 5900 K
		231 --> 235	White 7 : 6500 K
		236 --> 240	White 8 : 7200 K
		241 --> 245	White 9 : 8000 K
		246 --> 250	White 10 : 8500 K
251 --> 255	White 11 : 10000 K		
15	Rings Effect	0 --> 9	Safe
		10 --> 19	Static Ring 1
		20 --> 29	Static Ring 2
		30 --> 39	Static Ring 3u
		40 --> 49	Static Ring 3d
		50 --> 59	Static Ring 4u
		60 --> 69	Static Ring 4d
		70 --> 79	Effect 1
		80 --> 89	Effect 2
		90 --> 99	Effect 3
		100 --> 109	Effect 4
		110 --> 119	Effect 5
		120 --> 129	Effect 6
		130 --> 139	Effect 7
		140 --> 149	Effect 8
		150 --> 159	Effect 9
160 --> 169	Effect 10		

		170 --> 179	Effect 11
		180 --> 189	Effect 12
		190 --> 199	Effect 13
		200 --> 209	Effect 14
		210 --> 219	Effect 15
		220 --> 229	Effect 16
		230 --> 239	Effect 17
		240 --> 249	Effect 18
		250 --> 255	Effect 19
16	Effect Speed	0 --> 255	0% to 100% Effect Speed
17	Dimmer	0 --> 255	0% to 100% Dimmer
18	Dimmer Fine	0 --> 255	Dimmer Fine
19	Strobe	0 --> 9	Safe
		10 --> 255	0 Hz to 20Hz Strobe
20	Zoom	0 --> 255	0% to 100% Zoom
21	Control	0 --> 19	Safe
		20 --> 39	Move in Dark ON
		40 --> 59	Move in Dark OFF
		60 --> 79	Fan Auto
		80 --> 99	Fan Slow
		100 --> 119	Fan Normal
		120 --> 139	Fan Fast
		140 --> 149	Auto 1
		150 --> 159	Auto 2
		160 --> 169	Test
		170 --> 179	Custom
		180 --> 199	Safe
		200 --> 219	Reset
		220 --> 235	Safe
		236 --> 239	Dim 0
		240 --> 243	Dim 1
244 --> 247	Dim 2		
248 --> 251	Dim 3		
252 --> 255	Dim 4		

Person 3 : 8 Ch

Channel	Function	Value	Description
1	Pan	0 --> 255	540° Pan
2	Tilt	0 --> 255	270° Tilt
3	Hue	0 --> 255	0% to 100% Color Hue
4	Saturation	0 --> 255	0% to 100% Color Saturation
5	Dimmer	0 --> 255	0% to 100% Dimmer
6	Strobe	0 --> 9	Safe
		10 --> 255	0 Hz to 20Hz Strobe

7	Zoom	0 --> 255	0% to 100% Zoom
8	Control	0 --> 19	Safe
		20 --> 39	Move in Dark ON
		40 --> 59	Move in Dark OFF
		60 --> 79	Fan Auto
		80 --> 99	Fan Slow
		100 --> 119	Fan Normal
		120 --> 139	Fan Fast
		140 --> 149	Auto 1
		150 --> 159	Auto 2
		160 --> 169	Test
		170 --> 179	Custom
		180 --> 199	Safe
		200 --> 219	Reset
		220 --> 235	Safe
		236 --> 239	Dim 0
240 --> 243	Dim 1		
244 --> 247	Dim 2		
248 --> 251	Dim 3		
		252 --> 255	Dim 4

Person 4 : 21 Ch

Channel	Function	Value	Description
1	Pan	0 --> 255	540° Pan
2	Pan Fine	0 --> 255	Pan Fine
3	Tilt	0 --> 255	270° Tilt
4	Tilt Fine	0 --> 255	Tilt Fine
5	P/T Speed	0 --> 255	Pan and Tilt Speed
6	Dimmer	0 --> 255	0% to 100% Dimmer
7	Strobe	0 --> 9	Safe
		10 --> 255	0 Hz to 20Hz Strobe
8	Zoom	0 --> 255	0% to 100% Zoom
9	Control	0 --> 19	Safe
		20 --> 39	Move in Dark ON
		40 --> 59	Move in Dark OFF
		60 --> 79	Fan Auto
		80 --> 99	Fan Slow
		100 --> 119	Fan Normal
		120 --> 139	Fan Fast
		140 --> 149	Auto 1
		150 --> 159	Auto 2
		160 --> 169	Test
		170 --> 179	Custom
		180 --> 199	Safe
		200 --> 219	Reset
		220 --> 235	Safe

		236 --> 239	Dim 0
		240 --> 243	Dim 1
		244 --> 247	Dim 2
		248 --> 251	Dim 3
		252 --> 255	Dim 4
10	Red 1	0 --> 255	0% to 100% Red LEDs
11	Green 1	0 --> 255	0% to 100% Green LEDs
12	Blue 1	0 --> 255	0% to 100% Blue LEDs
13	White 1	0 --> 255	0% to 100% White LEDs
14	Red 2	0 --> 255	0% to 100% Red LEDs
15	Green 2	0 --> 255	0% to 100% Green LEDs
16	Blue 2	0 --> 255	0% to 100% Blue LEDs
17	White 2	0 --> 255	0% to 100% White LEDs
18	Red 3	0 --> 255	0% to 100% Red LEDs
19	Green 3	0 --> 255	0% to 100% Green LEDs
20	Blue 3	0 --> 255	0% to 100% Blue LEDs
21	White 3	0 --> 255	0% to 100% White LEDs

<b>Person 5 : 34 Ch</b>
-------------------------

Channel	Function	Value	Description
1	Pan	0 --> 255	540° Pan
2	Pan Fine	0 --> 255	Pan Fine
3	Tilt	0 --> 255	270° Tilt
4	Tilt Fine	0 --> 255	Tilt Fine
5	P/T Speed	0 --> 255	Pan and Tilt Speed
6	Dimmer	0 --> 255	0% to 100% Dimmer
7	Dimmer Fine	0 --> 255	Dimmer Fine
8	Strobe	0 --> 9	Safe
		10 --> 255	0 Hz to 20Hz Strobe
9	Zoom	0 --> 255	0% to 100% Zoom
10	Control	0 --> 19	Safe
		20 --> 39	Move in Dark ON
		40 --> 59	Move in Dark OFF
		60 --> 79	Fan Auto
		80 --> 99	Fan Slow
		100 --> 119	Fan Normal
		120 --> 139	Fan Fast
		140 --> 149	Auto 1
		150 --> 159	Auto 2
		160 --> 169	Test
		170 --> 179	Custom
		180 --> 199	Safe
		200 --> 219	Reset
220 --> 235	Safe		

		236 --> 239	Dim 0
		240 --> 243	Dim 1
		244 --> 247	Dim 2
		248 --> 251	Dim 3
		252 --> 255	Dim 4
11	Red 1	0 --> 255	0% to 100% Red LEDs
12	Red 1 Fine	0 --> 255	Red Fine
13	Green 1	0 --> 255	0% to 100% Green LEDs
14	Green 1 Fine	0 --> 255	Green Fine
15	Blue 1	0 --> 255	0% to 100% Blue LEDs
16	Blue 1 Fine	0 --> 255	Blue Fine
17	White 1	0 --> 255	0% to 100% White LEDs
18	White 1 Fine	0 --> 255	White Fine
19	Red 2	0 --> 255	0% to 100% Red LEDs
20	Red 2 Fine	0 --> 255	Red Fine
21	Green 2	0 --> 255	0% to 100% Green LEDs
22	Green 2 Fine	0 --> 255	Green Fine
23	Blue 2	0 --> 255	0% to 100% Blue LEDs
24	Blue 2 Fine	0 --> 255	Blue Fine
25	White 2	0 --> 255	0% to 100% White LEDs
26	White 2 Fine	0 --> 255	White Fine
27	Red 3	0 --> 255	0% to 100% Red LEDs
28	Red 3 Fine	0 --> 255	Red Fine
29	Green 3	0 --> 255	0% to 100% Green LEDs
30	Green 3 Fine	0 --> 255	Green Fine
31	Blue 3	0 --> 255	0% to 100% Blue LEDs
32	Blue 3 Fine	0 --> 255	Blue Fine
33	White 3	0 --> 255	0% to 100% White LEDs
34	White 3 Fine	0 --> 255	White Fine