

Flash 5 RGBW

2 Modes 4 - 8

4 CHs

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Green	0 --> 255	0% to 100% Green LEDs
3	Blue	0 --> 255	0% to 100% Blue LEDs
4	White	0 --> 255	0% to 100% White LEDs

8 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Red	0 --> 255	0% to 100% Red LEDs
3	Green	0 --> 255	0% to 100% Green LEDs
4	Blue	0 --> 255	0% to 100% Blue LEDs
5	White	0 --> 255	0% to 100% White LEDs
7	Macro	0 --> 50	Safe
		51 --> 100	Color Macro
		101 --> 150	Color Jump
		151 --> 200	Color Gradient
		201 --> 250	Color Pulse
		251 --> 255	Sound Mode
8	Speed	0 --> 255	Dimmer Speed / Macro Effect Speed