

Flash 55

9 Modes 4 - 4 - 6 - 10 - 14 - 16 - 48 - 50 - 64

4 CHs

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Green	0 --> 255	0% to 100% Green LEDs
3	Blue	0 --> 255	0% to 100% Blue LEDs
4	White	0 --> 255	0% to 100% White LEDs

4 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 250	Slow to Fast Strobe (1-20 Hz)
		251 --> 255	Open
3	Duration	0 --> 255	Flash Duration (0 to 510 ms)
4	Color Macro	0 --> 5	Open
		6 --> 13	Red
		14 --> 21	Amber
		22 --> 29	Yellow Amber
		30 --> 37	Yellow
		38 --> 45	Green
		46 --> 53	Turquoise
		54 --> 61	Cyan
		62 --> 69	Blue
		70 --> 77	Lavender
		78 --> 85	Mauve
		86 --> 93	Magenta
		94 --> 101	Pink
		102 --> 109	Warm White
		110 --> 117	White
		118 --> 125	Cool White
126 --> 127	Safe		
128 --> 191	Slow to Fast Color Jump		
192 --> 255	Slow to Fast Color Fade		

6 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 33	Slow to Fast Random Pulse
		34 --> 56	Slow to Fast Random Open Pulse
		57 --> 79	Slow to Fast Random Close Pulse
		80 --> 102	Slow to Fast Random Strobe
		103 --> 127	Slow to Fast Burst
		128 --> 250	Slow to Fast Strobe (1-20 Hz)
251 --> 255	Open		
3	Red	0 --> 255	0% to 100% Red LEDs
4	Green	0 --> 255	0% to 100% Green LEDs
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	White	0 --> 255	0% to 100% White LEDs

10 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 33	Slow to Fast Random Pulse
		34 --> 56	Slow to Fast Random Open Pulse
		57 --> 79	Slow to Fast Random Close Pulse
		80 --> 102	Slow to Fast Random Strobe
		103 --> 127	Slow to Fast Burst
		128 --> 250	Slow to Fast Strobe (1-20 Hz)
251 --> 255	Open		
3	Red	0 --> 255	0% to 100% Group 1 Red LEDs
4	Green	0 --> 255	0% to 100% Group 1 Green LEDs
5	Blue	0 --> 255	0% to 100% Group 1 Blue LEDs
6	White	0 --> 255	0% to 100% Group 1 White LEDs
7	Red	0 --> 255	0% to 100% Group 2 Red LEDs
8	Green	0 --> 255	0% to 100% Group 2 Green LEDs
9	Blue	0 --> 255	0% to 100% Group 2 Blue LEDs
10	White	0 --> 255	0% to 100% Group 2 White LEDs

14 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 33	Slow to Fast Random Pulse
		34 --> 56	Slow to Fast Random Open Pulse
		57 --> 79	Slow to Fast Random Close Pulse
		80 --> 102	Slow to Fast Random Strobe
		103 --> 127	Slow to Fast Burst
		128 --> 250	Slow to Fast Strobe (1-20 Hz)
251 --> 255	Open		
3	Red	0 --> 255	0% to 100% Group 1 Red LEDs
4	Green	0 --> 255	0% to 100% Group 1 Green LEDs
5	Blue	0 --> 255	0% to 100% Group 1 Blue LEDs
6	White	0 --> 255	0% to 100% Group 1 White LEDs
7	Red	0 --> 255	0% to 100% Group 2 Red LEDs
8	Green	0 --> 255	0% to 100% Group 2 Green LEDs
9	Blue	0 --> 255	0% to 100% Group 2 Blue LEDs
10	White	0 --> 255	0% to 100% Group 2 White LEDs
11	Red	0 --> 255	0% to 100% Group 3 Red LEDs
12	Green	0 --> 255	0% to 100% Group 3 Green LEDs
13	Blue	0 --> 255	0% to 100% Group 3 Blue LEDs
14	White	0 --> 255	0% to 100% Group 3 White LEDs

16 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 33	Slow to Fast Random Pulse
		34 --> 56	Slow to Fast Random Open Pulse
		57 --> 79	Slow to Fast Random Close Pulse
		80 --> 102	Slow to Fast Random Strobe
		103 --> 127	Slow to Fast Burst
		128 --> 250	Slow to Fast Strobe (1-20 Hz)
251 --> 255	Open		
3	Red	0 --> 255	0% to 100% Red LEDs
4	Green	0 --> 255	0% to 100% Green LEDs
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	White	0 --> 255	0% to 100% White LEDs

7	Color Macro	0 --> 5	Open
		6 --> 13	Red
		14 --> 21	Amber
		22 --> 29	Yello Amber
		30 --> 37	Yellow
		38 --> 45	Green
		46 --> 53	Turquoise
		54 --> 61	Cyan
		62 --> 69	Blue
		70 --> 77	Lavender
		78 --> 85	Mauve
		86 --> 93	Magenta
		94 --> 101	Pink
		102 --> 109	Warm White
		110 --> 117	White
		118 --> 125	Cool White
		126 --> 127	Safe
		128 --> 191	Slow to Fast Color Jump
		192 --> 255	Slow to Fast Color Fade
		8	Macro
11 --> 22	Effect 1		
23 --> 34	Effect 2		
35 --> 46	Effect 3		
47 --> 58	Effect 4		
59 --> 70	Effect 5		
71 --> 82	Effect 6		
83 --> 94	Effect 7		
95 --> 106	Effect 8		
107 --> 118	Effect 9		
119 --> 130	Effect 10		
131 --> 142	Effect 11		
143 --> 154	Effect 12		
155 --> 166	Effect 13		
167 --> 178	Effect 14		
179 --> 190	Effect 15		
191 --> 202	Effect 16		
203 --> 214	Effect 17		
215 --> 226	Effect 18		
227 --> 238	Effect 19		
239 --> 255	Effect 20		

9	Speed	0 --> 125	Fast to Slow CCW Effect
		126 --> 130	Stop
		131 --> 255	Slow to Fast CW Effect
10	Rainbow	0 --> 5	Open
		11 --> 22	Rainbow 1
		23 --> 34	Rainbow 2
		35 --> 46	Rainbow 3
		47 --> 58	Rainbow 4
		59 --> 70	Rainbow 5
		71 --> 82	Rainbow 6
		83 --> 94	Rainbow 7
		95 --> 106	Rainbow 8
		107 --> 118	Rainbow 9
		119 --> 130	Rainbow 10
		131 --> 142	Rainbow 11
		143 --> 154	Rainbow 12
		155 --> 166	Rainbow 13
		167 --> 178	Rainbow 14
		179 --> 190	Rainbow 15
		191 --> 202	Rainbow 16
		203 --> 214	Rainbow 17
		215 --> 226	Rainbow 18
		227 --> 238	Rainbow 19
239 --> 255	Rainbow 20		
11	Control	0 --> 5	Safe
		6 --> 63	LED Dimmer
		64 --> 127	Halogen Dimmer
		128 --> 191	High Fan
		192 --> 255	Auto Fan
12	Back Dimmer	0 --> 255	0% to 100% Background Dimmer
13	Back Red	0 --> 255	0% to 100% Background Red
14	Back Green	0 --> 255	0% to 100% Background Green
15	Back Blue	0 --> 255	0% to 100% Background Blue
16	Back White	0 --> 255	0% to 100% Background White

48 CHs

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Group 1 Red LEDs
2	Green	0 --> 255	0% to 100% Group 1 Green LEDs
3	Blue	0 --> 255	0% to 100% Group 1 Blue LEDs
4	White	0 --> 255	0% to 100% Group 1 White LEDs
5	Red	0 --> 255	0% to 100% Group 2 Red LEDs
6	Green	0 --> 255	0% to 100% Group 2 Green LEDs
7	Blue	0 --> 255	0% to 100% Group 2 Blue LEDs
8	White	0 --> 255	0% to 100% Group 2 White LEDs
...
41	Red	0 --> 255	0% to 100% Group 11 Red LEDs
42	Green	0 --> 255	0% to 100% Group 11 Green LEDs
43	Blue	0 --> 255	0% to 100% Group 11 Blue LEDs
44	White	0 --> 255	0% to 100% Group 11 White LEDs
45	Red	0 --> 255	0% to 100% Group 12 Red LEDs
46	Green	0 --> 255	0% to 100% Group 12 Green LEDs
47	Blue	0 --> 255	0% to 100% Group 12 Blue LEDs
48	White	0 --> 255	0% to 100% Group 12 White LEDs

50 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 33	Slow to Fast Random Pulse
		34 --> 56	Slow to Fast Random Open Pulse
		57 --> 79	Slow to Fast Random Close Pulse
		80 --> 102	Slow to Fast Random Strobe
		103 --> 127	Slow to Fast Burst
		128 --> 250	Slow to Fast Strobe (1-20 Hz)
		251 --> 255	Open
3	Red	0 --> 255	0% to 100% Group 1 Red LEDs
4	Green	0 --> 255	0% to 100% Group 1 Green LEDs
5	Blue	0 --> 255	0% to 100% Group 1 Blue LEDs
6	White	0 --> 255	0% to 100% Group 1 White LEDs
7	Red	0 --> 255	0% to 100% Group 2 Red LEDs
8	Green	0 --> 255	0% to 100% Group 2 Green LEDs
9	Blue	0 --> 255	0% to 100% Group 2 Blue LEDs
10	White	0 --> 255	0% to 100% Group 2 White LEDs
...
43	Red	0 --> 255	0% to 100% Group 11 Red LEDs
44	Green	0 --> 255	0% to 100% Group 11 Green LEDs
45	Blue	0 --> 255	0% to 100% Group 11 Blue LEDs
46	White	0 --> 255	0% to 100% Group 11 White LEDs
47	Red	0 --> 255	0% to 100% Group 12 Red LEDs
48	Green	0 --> 255	0% to 100% Group 12 Green LEDs
49	Blue	0 --> 255	0% to 100% Group 12 Blue LEDs
50	White	0 --> 255	0% to 100% Group 12 White LEDs

64 CHs

Channel	Function	Value	Description
1	Dimmer	0 --> 255	0% to 100% Dimmer
2	Strobe	0 --> 5	Open
		6 --> 10	Close
		11 --> 33	Slow to Fast Random Pulse
		34 --> 56	Slow to Fast Random Open Pulse
		57 --> 79	Slow to Fast Random Close Pulse
		80 --> 102	Slow to Fast Random Strobe
		103 --> 127	Slow to Fast Burst
		128 --> 250	Slow to Fast Strobe (1-20 Hz)
		251 --> 255	Open
3	Red	0 --> 255	0% to 100% Red LEDs
4	Green	0 --> 255	0% to 100% Green LEDs
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	White	0 --> 255	0% to 100% White LEDs
7	Color Macro	0 --> 5	Open
		6 --> 13	Red
		14 --> 21	Amber
		22 --> 29	Yellow Amber
		30 --> 37	Yellow
		38 --> 45	Green
		46 --> 53	Turquoise
		54 --> 61	Cyan
		62 --> 69	Blue
		70 --> 77	Lavender
		78 --> 85	Mauve
		86 --> 93	Magenta
		94 --> 101	Pink
		102 --> 109	Warm White
		110 --> 117	White
		118 --> 125	Cool White
		126 --> 127	Safe
128 --> 191	Slow to Fast Color Jump		
192 --> 255	Slow to Fast Color Fade		

8	Macro	0	Open
		11 --> 22	Effect 1
		23 --> 34	Effect 2
		35 --> 46	Effect 3
		47 --> 58	Effect 4
		59 --> 70	Effect 5
		71 --> 82	Effect 6
		83 --> 94	Effect 7
		95 --> 106	Effect 8
		107 --> 118	Effect 9
		119 --> 130	Effect 10
		131 --> 142	Effect 11
		143 --> 154	Effect 12
		155 --> 166	Effect 13
		167 --> 178	Effect 14
		179 --> 190	Effect 15
		191 --> 202	Effect 16
		203 --> 214	Effect 17
		215 --> 226	Effect 18
		227 --> 238	Effect 19
239 --> 255	Effect 20		
9	Speed	0 --> 125	Fast to Slow CCW Effect
		126 --> 130	Stop
		131 --> 255	Slow to Fast CW Effect
10	Rainbow	0 --> 5	Open
		11 --> 22	Rainbow 1
		23 --> 34	Rainbow 2
		35 --> 46	Rainbow 3
		47 --> 58	Rainbow 4
		59 --> 70	Rainbow 5
		71 --> 82	Rainbow 6
		83 --> 94	Rainbow 7
		95 --> 106	Rainbow 8
		107 --> 118	Rainbow 9
		119 --> 130	Rainbow 10
		131 --> 142	Rainbow 11
		143 --> 154	Rainbow 12
		155 --> 166	Rainbow 13
		167 --> 178	Rainbow 14
		179 --> 190	Rainbow 15
		191 --> 202	Rainbow 16
		203 --> 214	Rainbow 17
		215 --> 226	Rainbow 18
		227 --> 238	Rainbow 19
239 --> 255	Rainbow 20		

11	Control	0 --> 5	Safe
		6 --> 63	LED Dimmer
		64 --> 127	Halogen Dimmer
		128 --> 191	High Fan
		192 --> 255	Auto Fan
12	Back Dimmer	0 --> 255	0% to 100% Background Dimmer
13	Back Red	0 --> 255	0% to 100% Background Red
14	Back Green	0 --> 255	0% to 100% Background Green
15	Back Blue	0 --> 255	0% to 100% Background Blue
16	Back White	0 --> 255	0% to 100% Background White
17	Red	0 --> 255	0% to 100% Group 1 Red LEDs
18	Green	0 --> 255	0% to 100% Group 1 Green LEDs
19	Blue	0 --> 255	0% to 100% Group 1 Blue LEDs
20	White	0 --> 255	0% to 100% Group 1 White LEDs
21	Red	0 --> 255	0% to 100% Group 2 Red LEDs
22	Green	0 --> 255	0% to 100% Group 2 Green LEDs
23	Blue	0 --> 255	0% to 100% Group 2 Blue LEDs
24	White	0 --> 255	0% to 100% Group 2 White LEDs
...
47	Red	0 --> 255	0% to 100% Group 11 Red LEDs
48	Green	0 --> 255	0% to 100% Group 11 Green LEDs
49	Blue	0 --> 255	0% to 100% Group 11 Blue LEDs
60	White	0 --> 255	0% to 100% Group 11 White LEDs
61	Red	0 --> 255	0% to 100% Group 12 Red LEDs
62	Green	0 --> 255	0% to 100% Group 12 Green LEDs
63	Blue	0 --> 255	0% to 100% Group 12 Blue LEDs
64	White	0 --> 255	0% to 100% Group 12 White LEDs