



## Comet 1000

1 Mode 13

13 CHs

Channel	Function	Value	Description
1	Mode	0 --> 9	Safe ( <i>Power on value</i> )
		10 --> 99	Auto Mode
		100 --> 199	Sound Mode
		200 --> 255	DMX Mode ( <i>Locate value</i> )
2	Shape Selection	0 --> 255	Shape selection
3	Zoom	0 --> 63	Index
		64 --> 127	Slow to Fast Zoom Out Animation
		128 --> 191	Slow to Fast Zoom In Animation
		192 --> 255	Slow to Fast Zoom In/Out Animation
4	Center Rotation	0 --> 127	Index
		128 --> 191	Slow to Fast CW Rotation
		192 --> 255	Slow to Fast CCW Rotation
5	Pan Rotation	0 --> 127	Index
		128 --> 191	Slow to Fast CW Rotation
		192 --> 255	Slow to Fast CCW Rotation
6	Tilt Rotation	0 --> 127	Index
		128 --> 191	Slow to Fast CW Rotation
		192 --> 255	Slow to Fast CCW Rotation
7	Pan Scanner	0 --> 127	Index
		128 --> 255	Slow to Fast Pan Animation
8	Tilt Scanner	0 --> 127	Index
		128 --> 255	Slow to Fast Tilt Animation
9	Wave	0 --> 1	Safe
		2 --> 127	Index
		128 --> 255	Slow to Fast Wave

		0 --> 9	Safe
10	Trace	10 --> 63	Index
		64 --> 127	Slow to Fast Positive Trace
		128 --> 191	Slow to Fast Negative Trace
		192 --> 255	Slow to Fast Bounce Trace
11	Color	0 --> 127	Color Macros
		128 --> 159	Color Change
		160 --> 191	Mode 1 Color Change with Split
		192 --> 249	Mode 2 Color Change with Split
		250 --> 255	Mode 3 Color Change with Split
12	Color Speed	0 --> 9	Safe
		10 --> 255	Slow to Fast Color Change
13	Display Mode	0 --> 63	Full Linear
		64 --> 127	Linear + Dots
		128 --> 255	Dots