

Sparkly 800 Wash

3 Modes 20 - 30 - 77

20 Channels

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Red	0 --> 255	Red Fine
3	Green	0 --> 255	0% to 100% Green LEDs
4	Green	0 --> 255	Green Fine
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	Blue	0 --> 255	Blue Fine
7	White	0 --> 255	0% to 100% White LEDs
8	White	0 --> 255	White Fine
9	White Temp.	0 --> 255	White Colour Temperature
10	Colour Macro	0 --> 255	Colors Macros
11	Strobe	0	Close
		4 --> 103	Slow to Fast Strobe
		108 --> 207	Slow to Fast Pulse
		213 --> 225	Slow Random Strobe
		226 --> 238	Medium Random Strobe
		239 --> 251	Fast Random Strobe
		255	Open
12	Dimmer	0 --> 255	0% to 100% Dimmer
13	Dimmer Fine	0 --> 255	Dimmer Fine
14	Pan	0 --> 255	540° Pan
15	Pan Fine	0 --> 255	Pan Fine
16	Tilt	0 --> 255	270° Tilt
17	Tilt Fine	0 --> 255	Tilt Fine
18	Function	0 --> 255	Reserved
19	Control	0	Safe
		26 --> 76	Reset Zoom
		77 --> 127	Reset P/T
		128 --> 255	Reset All
20	Zoom	0 --> 255	0% to 100% Zoom

30 Channels

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Red	0 --> 255	Red Fine
3	Green	0 --> 255	0% to 100% Green LEDs
4	Green	0 --> 255	Green Fine
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	Blue	0 --> 255	Blue Fine
7	White	0 --> 255	0% to 100% White LEDs
8	White	0 --> 255	White Fine
9	White Temp.	0 --> 255	White Colour Temperature
10	Colour Macro	0 --> 255	Colors Macros
11	Strobe	0	Close
		4 --> 103	Slow to Fast Strobe
		108 --> 207	Slow to Fast Pulse
		213 --> 225	Slow Random Strobe
		226 --> 238	Medium Random Strobe
		239 --> 251	Fast Random Strobe
		255	Open
12	Dimmer	0 --> 255	0% to 100% Dimmer
13	Dimmer Fine	0 --> 255	Dimmer Fine
14	Pan	0 --> 255	540° Pan
15	Pan Fine	0 --> 255	Pan Fine
16	Tilt	0 --> 255	270° Tilt
17	Tilt Fine	0 --> 255	Tilt Fine
18	Function	0 --> 255	Reserved
19	Control	0	Safe
		26 --> 76	Reset Zoom
		77 --> 127	Reset P/T
		128 --> 255	Reset All
20	Zoom	0 --> 255	0% to 100% Zoom
21	Fixed Shape	0 --> 4	Open
		6 --> 9	Shape 1
		10 --> 14	Shape 2
		15 --> 19	Shape 3
		20 --> 24	Shape 4
	
		185 --> 189	Shape 37
		190 --> 204	Shape 38
		205 --> 224	Fast to Slow CW Shape Scroll
		225 --> 234	Safe
		244 --> 255	Slow to Fast CCW Shape Scroll

22	Pixel Effect	0 --> 4	Open
		6 --> 14	Effect 1
		15 --> 24	Effect 2
		25 --> 34	Effect 3
		35 --> 44	Effect 4
	
		165 --> 174	Effect 18
		185 --> 194	Effect 19
		195 --> 204	Effect 20
23	Effect Speed	0 --> 127	Fast to Slow FW Effect
		128 --> 255	Slow to Fast BKW Effect
24	Motion Blur	0 --> 255	0% to 100% Effect Motion Blur
25	Effect Red	0 --> 255	0% to 100% Red LEDs
26	Effect Green	0 --> 255	0% to 100% Green LEDs
27	Effect Blue	0 --> 255	0% to 100% Blue LEDs
28	Effect White	0 --> 255	0% to 100% White LEDs
29	Effect Dimmer	0 --> 255	0% to 100% Effect Dimmer
30	Back Dimmer	0 --> 255	0% to 100% Background Dimmer

77 Channels

Channel	Function	Value	Description
1	Red	0 --> 255	0% to 100% Red LEDs
2	Red	0 --> 255	Red Fine
3	Green	0 --> 255	0% to 100% Green LEDs
4	Green	0 --> 255	Green Fine
5	Blue	0 --> 255	0% to 100% Blue LEDs
6	Blue	0 --> 255	Blue Fine
7	White	0 --> 255	0% to 100% White LEDs
8	White	0 --> 255	White Fine
9	White Temp.	0 --> 255	White Colour Temperature
10	Colour Macro	0 --> 255	Colors Macros
11	Strobe	0	Close
		4 --> 103	Slow to Fast Strobe
		108 --> 207	Slow to Fast Pulse
		213 --> 225	Slow Random Strobe
		226 --> 238	Medium Random Strobe
		239 --> 251	Fast Random Strobe
		255	Open
12	Dimmer	0 --> 255	0% to 100% Dimmer
13	Dimmer Fine	0 --> 255	Dimmer Fine
14	Pan	0 --> 255	540° Pan
15	Pan Fine	0 --> 255	Pan Fine
16	Tilt	0 --> 255	270° Tilt
17	Tilt Fine	0 --> 255	Tilt Fine
18	Function	0 --> 255	Reserved

19	Control	0	Safe
		26 --> 76	Reset Zoom
		77 --> 127	Reset P/T
		128 --> 255	Reset All
20	Zoom	0 --> 255	0% to 100% Zoom
21	Red	0 --> 255	0% to 100% Cell 1 Red LEDs
22	Green	0 --> 255	0% to 100% Cell 1 Green LEDs
23	Blue	0 --> 255	0% to 100% Cell 1 Blue LEDs
24	Red	0 --> 255	0% to 100% Cell 2 Red LEDs
25	Green	0 --> 255	0% to 100% Cell 2 Green LEDs
26	Blue	0 --> 255	0% to 100% Cell 2 Blue LEDs
27	Red	0 --> 255	0% to 100% Cell 3 Red LEDs
28	Green	0 --> 255	0% to 100% Cell 3 Green LEDs
29	Blue	0 --> 255	0% to 100% Cell 3 Blue LEDs
...
72	Red	0 --> 255	0% to 100% Cell 18 Red LEDs
73	Green	0 --> 255	0% to 100% Cell 18 Green LEDs
74	Blue	0 --> 255	0% to 100% Cell 18 Blue LEDs
75	Red	0 --> 255	0% to 100% Cell 19 Red LEDs
76	Green	0 --> 255	0% to 100% Cell 19 Green LEDs
77	Blue	0 --> 255	0% to 100% Cell 19 Blue LEDs